



# Revelation<sup>2</sup>

## *Stereo and Monoblock Amplifiers*

---

The Constellation Revelation 2 Stereo and Monoblock Amplifiers express the power and passion of the Performance 2 amplifiers in a more compact chassis. Their sound is taken to a new level with our revolutionary Switch-Mode Power Supply. Balanced Bridged technology utilizes single-ended amplifier modules, which deliver impressive output while driving any speaker with the subtlety of a small amplifier.



# Revelation<sup>2</sup> Stereo and Monoblock Amplifiers



## The Input Stage

The same Line Stage Gain Module input stage found in Constellation's top amplifiers utilizes hand-matched, low-noise transistors combined with a servo circuit that corrects any signal balance inconsistencies. The Constellation Direct XLR input removes one amplification stage from the signal path for less complexity and even greater musicality.

## The Power Supply

Our Constellation Switch-Mode Power Supply (C-SMPS) rises above the century-old technologies that hinder the performance of traditional amplifiers, with over 20 dB less noise than a typical linear supply. Power Factor Correction (PFC) technology provides stable power at any AC supply voltage—worldwide. Voltage and current are always in phase regardless of speaker load, while power over the previous version is increased by 20 percent.

## The Circuit

Revelation 2 amplifiers employ a balanced configuration, with separate amplifier circuits for the positive and negative halves of the audio signal.

Other balanced amplifiers use N-type transistors for the positive half of the circuit and P-type transistors for the negative half. Our Balanced Bridged configuration uses only N-type transistors, so both signal halves pass through exactly the same circuitry—with even the softest musical details preserved.

## The Result

Both Revelation 2 amplifiers are essentially distilled versions of our Performance 2, sharing the same circuits and core design philosophy. In fact, they're perfect examples of why Constellation's approach to amplification works so well. Instead of redesigning the amplifiers to make them smaller, our engineers simply reduced the number of modules to deliver the desired power output.

Through a combination of Constellation's innovative audio circuits and revolutionary C-SMPS power supply, the Revelation 2 amplifiers achieve astounding sonic results. And while smaller in stature than our Performance 2 amplifiers, their musicality and emotion remain undiminished.

## Specifications

### Stereo Amplifier

**Inputs:** 4 XLR (2 Direct), 2 RCA

**Max power @ 8  $\Omega$  (0.1% THD+N, 20 Hz–20 kHz):** 300 WPC

**Max power @ 4  $\Omega$  (0.1% THD+N, 20 Hz–20 kHz):** 600 WPC

**Input sensitivity @ max power at 0.1% into 8  $\Omega$ :** 15 V direct i/p, 3 V non-direct

**Input sensitivity @ max power at 0.1% into 4  $\Omega$ :** 12.5 V direct i/p, 2.6 V non-direct

### Monoblock Amplifier

**Inputs:** 2 XLR (1 Direct), 1 RCA

**Max power @ 8  $\Omega$  (0.1% THD+N, 20 Hz–20 kHz):** 600 W

**Max power @ 4  $\Omega$  (0.1% THD+N, 20 Hz–20 kHz):** 1,100 W

**Input sensitivity @ max power at 0.1% into 8  $\Omega$ :** 17.8 V direct i/p, 3.5 V non-direct

**Input sensitivity @ max power at 0.1% into 4  $\Omega$ :** 16 V direct i/p, 3.5 V non-direct

**Frequency response:** 10 Hz–80 kHz +/- 0.05 dB

**Gain, direct input:** 12 dB

**Gain, non-direct input:** 25.2 dB

**AC power draw, standby:** <0.5 W

**AC power draw, idle:** 135 W

**AC power draw @ max power into 8  $\Omega$ :** 1,300 W

**AC power draw @ max power into 4  $\Omega$ :** 1,970 W

**Power factor, partial power:** 0.98

**Power factor, full power:** 1.0

**Damping factor:** >150

**Signal-to-noise ratio, DC-90 kHz ref 1 V:** >100 dB, A-weighted

**Signal-to-noise ratio, DC-90 kHz ref full power:** >115 dB, unweighted

**Signal-to-noise ratio, DC-90 kHz ref full power:** >125 dB, A-weighted

**Output impedance:** 0.05  $\Omega$

**Weight:** 55 lbs / 25 kg

**Dimensions:** 17 x 8.5 x 23 in / 43.2 x 21.6 x 58.4 cm (WHD)

*Specifications subject to change.*



[sales@constellationaudio.com](mailto:sales@constellationaudio.com)



**C Switch-Mode**  
POWER SUPPLY

Precise, Consistent Power Delivery